



Security World, Inc.

10 Cedar Street Valhalla, NY 10595

914-761-9500

ALARM SYSTEM INSTRUCTIONS

To Arm:

- A. When leaving (with motion detectors)
Make sure Green Ready light is lit before arming. If green light is not on press * to show zones not ready (those zones must be closed before arming).
1. Press AWAY button until beep and the green light changes red, you now have 60 seconds to exit.
 2. OR, your code & 2 (ex: 1-2-3-4-2)
- B. When Staying on premises (with out motion detectors)
1. Press STAY button until beep, you now have 60 seconds to exit premises. It will also give you 30 seconds when re-entering thru a delayed door to disarm system.
 2. Press # + 7, *INSTANT ALARM*, This will not give any time for entry, it will instantly go into alarm when any door or window is opened. This is best used for Sleep Mode and no one else entering the house.
- C. To Bypass an Open Zone
1. Press * to determine open zone(s). To bypass that zone, enter your user code + 6 + zone number as displayed on keypad (i.e. 02, 03, 10) Note: You must do this step for each zone you want to bypass. System will beep and show bypassed zone(s). Now you should have green ready light to arm. See above instructions for arming.

To Disarm:

- A. Enter your user code + 1. *This can be used to silence alarm for any reason.*

Resetting Alarm after an Activation

- A. Enter your user code + 1 two times to clear the alarms. (i.e. Disarm the system twice)

Chime Mode

- A. To Turn On/Off

1. Enter your user code + 9. Keypad window will display CHIME.

Panic

- A. To Send a Panic Signal

1. At the same time, push # & *. Monitoring station will not call the house, they will automatically dispatch police.

Change User Code

- A. **Enter your code, 8, 02** (this is the user #/space. i.e. if you want to change your babysitter code who is user 3, then you would enter 03 rather than 02 and so on), **new code, pause 1 second** – any longer and it won't take, **new code again and keypad will beep to verify acceptance of code.**